Boost from Low Input Voltage to 3.3-5.0V!

3Watt BUP Series



Input V

Vdc

1.3 - (4.2)

Input voltage range at 3.3V output ----- 1.3V-2.8V

Input voltage range at 5.0V output ----- 1.3V-4.2V

Note 2: Ripple noise, efficiency value is when input voltage is at 2.5V.







Load Reg. Ripple Noise

mVpp(tvp.

10

%(tvp.

82(86)

%(tvp.)

0.2

Minimum Size, Step-Up DC-DC Converter

Input: 1.3V to 4.2V Output: 3.3V (3.3V to 5.0V)

Models

BUP Series

input voltage.

BUP-3.3S0R9

BUP-3.3S0R9D

Voltage can be optionally set with external resistors. (Ex.: 3.3V, 4.0V, 5.0V)

Line Reg.

%(tvp.

0.3

Output I

0-0.9

Note 1: Regarding this converter, for normal operation the output voltage needs to be higher than that of the

- Efficiency 86% (at 0.7A load)
- Efficiency 90% (at 0.5A load)
- Latest Technology, Synchronous **Rectification Circuit**
- Non-Isolated Type Converter
- Wide Input Voltage Range
- Remote ON/OFF Control
- Adjustable Output Voltage
- High Reliability, High Performance
- -20°C to +70°C

(Temp Derating Required)

- RoHS Compliance

- Operating Temp Range
- Note 3: Efficiency () value is at 0.7A load. Note 4: Ripple noise is measured at 20MHz bandwidth.
- Note 5: Depending on the ambient air temp conditions, air flow cooling is required.

Output V

Vdc


3.3

(3.3-5.0)

Note 6: For this product, there is a limit of max. output current depending on the input voltage. Refer to the data sheet.


<Outline>

BUP-3.3S0R9 (SIP type)



Weight: 3g typ. Units: mm

BUP-3.3S0R9D (DIP type)



Pin	Function
1	ON/OFF
2	Vin
3	GND
4	Vout
5	V.ADJ
6	Test pin *1
7	NC

Weight: 3g typ.

→ Output ON → Output OFF ON: Between 1pin and 3pin (-0.3 to +0.4V)

*1 This pin is for testing. Do not connect to anywhere

Tr1

Load

<Standard Connection Diagram> +Vout BUP-3.3S0R9 Series C1 Vin + 100μF 100µF or more ON/OFF GND R1 value)

R1: Output Voltage

- When not using the ON/OFF control, keep the ON/OFF pin open.
- When not adjusting the output, keep the V.ADJ pin open.

Tr1

- Low impedance product should be used for the input capacitor (C1), and put close to the pins (2pin, 3pin).
- Be sure to use an input and output capacitor. Output capacitor: ESR≥25mΩ.

This catalogue is an outline of the products. When designing, be sure to refer to the data sheets